Standby 33 kVA
Diesel Generating Sets

APD 33 A

Engine : Aksa
Alternator : Aksa
Control System : P 602

ISO8528	This generator set has been designed to meet ISO 8528 regulation.
SZUTEST	This generator set is manufactured in facilities certified to ISO 9001.
CE	This generator set is available with CE certification.
2000/14/EC	Enclosed product is tested according to EU noise legislation 2000/14/EC

3 Phase Ratings, 50 Hz, PF 0,0

	Standby Rating (ESP)		Prime Rating (PRP)		
Voltage	kVA	kW	kVA	kW	Amp
400/230	33,00	26,40	30,00	24,00	43,00

Standby Rating (ESP): Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528. Overload is not allowed.

Prime Rating (PRP): Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528. 10 % overload capability is available for a period of 1 hour within 12-hour perod of operation,in accordance with ISO 3046.

STANDARD SPECIFICATIONS

Heavy duty, water cooled diesel engine
Radiator with mechanical fan
Protective grille for rotating and hot parts
Electric starter and charge alternator
Starting battery (with lead acid) including rack and cables
Engine coolant heater
Steel base frame and anti-vibration isolators
Spare external fuel tank (open set)
Flexible fuel connection hoses
Two bearing, class H alternator
Industrial exhaust silencer and steel bellows supplied separately
Static battery charger
Manual for application and installation

OPTIONAL EQUIPMENTS

ENGINE

- Remote Radiator Cooling
- Fuel-Water Seperator Filter

ALTERNATOR

- Anti-Condensation Heater
- Main line circuit breaker

CONTROL SYSTEM

- Charge Ammeter

OTHER ACCESSORIES

- Automatic or manual fuel filling system
- Enclosure: weater protective or sound attenuated
- Trailer
- Tool kit for maintenance
- Main Fuel Tank

TRANSFER SWITCH

- Three Pole Contactor
- Four Pole Contactor

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories witout prior notice.

APD 33 A

Engine : Aksa
Alternator : Aksa
Control System : P 602

DIESEL ENGINE SPECIFICATIONS

Manufacturer		Aksa
Model		A4CRX25T
No. of Cylinders and Build		4 Cylinder, In Line
Aspiration and Cooling		Turbo Charged
Maximum Standby Power		1500 rpm 29,70 kW [39,80HP]
Total Displacement	L	2,540
Bore and Stroke	mm	90 X 95
Compression Ratio		18.0:1
Rated Speed (rpm)	rpm	1500
Governor		Mechanical
Oil Capacity	L	8,50
Coolant Capacity	L	11,00
Intake Air Flow	m³ /min.	2,40
Radiator Cooling Air	m³ /min.	115,00
Exhaust Gas Flow	m³ /min.	6,10
Exhaust Gas Temperature	° C	420,00
Start System		12 V d.c.
Fuel Consumption	Load	%100
	L/h	6,80

ALTERNATOR SPECIFICATIONS

Make		Aksa
Model		AK225
Frequency	Hz	50
Power	kVA	31,30
Design		Brushless, 4 poles
Phase		3
Voltage	V	400/230
Current	A	45,00
Insulation Class		H
Excitation System		Electronic (AVR)

DIEMENSIONS AND WEIGHT

Open Type	Dry Weight	Lenght	Width	Height	Tank Capacity
	kg.	mm.	mm.	mm.	L
APD 33 A	680,00	1500,00	900,00	1060,00	95,00
Canopy	Dry Weight	Lenght	Width	Height	Tank Capacity
	kg.	mm.	mm.	mm.	L
ASM 3	800.00	1940	970	1220	95

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories witout prior notice.

APD 33 A

Engine : Aksa
Alternator : Aksa
Control System : P 602

P 602 - Control System

1 Main status display.
2 Display scroll button.
3 Page(information) button.
4 Common alarm indicator.
5 Status LED's.
6 Operation selecting buttons.

Devices

DSE, model 6020 Auto Mains Failure control module.
Battery charger input 198-264 volt , output 27,6 V 5 A (24 V) or 13,8 Volt 5A (12V)
Emergency stop push button and fuses for control circuits.

Construction and Finish

Components installed in sheet steel enclosure. Phosphate chemical, pre-coating of steel provides corrosion resistant surface. Polyester composite powder topcoat forms high gloss and extremely durable finish. Lockable and hinged panel door provides easy access to components.

Installation

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen.Set. from Alternator)

Generating Set Control Unit

The DSE 6020 is a standard control module for our generator sets up to 200kVA and it have been designed to start and stop diesel and gas generator sets. The DSE 6020 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts. Module monitors the mains supply and switch over to the generator when the mains power fails. The DSE6020 also indicates operational status and fault conditions, Automatically shutting down the Gen. Set and giving true first up fault condition of Gen. Set failure.The LCD display indicates the fault.

Standard Specifications

Microprocessor controlled.
LCD display makes information easy to read.
4-line, 64 x 132 pixel display.
Automatically transfers between mains (utilty) and generator power.
Manual programming on front panel.
User-friendly set-up and button layout.
Front panel programming.
Remote start.
Event logging (10)showing date and time.
Controls: Stop/Reset, Manual, Auto, Test, Start, buttons. An additional push button next to the LCD display is used to scroll through the modules' metering displays.

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories witout prior notice.

APD 33 A

Engine : Aksa
Alternator : Aksa
Control System : P 602

Instruments

ENGINE
ÞEngine speed.
ÞOil pressure.
ÞCoolant temperature.
ÞRun time.
ÞBattery volts.
ÞConfigurable timing.
GENERATOR
ÞVoltage (L-L, L-N).
ÞCurrent (L1-L2-L3).
ÞFrequency.
MAINS
ÞVoltage (L-L, L-N).
ÞFrequency.
ÞMains ready.
ÞMains enabled.
ÞGen. Set ready.
ÞGen. Set enabled.

Protection Circuits

WARNING
ÞCharge failure.
ÞBattery Low/High voltage.
ÞFail to stop.
ÞLow /High generator voltage.
ÞUnder/over generator frequency.
ÞOver /Under speed.
ÞLow oil pressure.
ÞHigh coolant temperature.
SHUT DOWNS
ÞFail to start.
ÞEmergency stop.
ÞLow oil pressure.
ÞHigh coolant temperature.
ÞOver /Under speed.
ÞUnder/over generator frequency.
ÞUnder/over generator voltage.
ÞOil pressure sensor open.
ÞCoolant temperature sensor open.
ELECTRICAL TRIP
ÞGenerator over current.

Options

ÞFlexible sensor can be controlled with temperature, pressure, percentage (warning/shutdown/electrical trip)
ÞLocal setting parameters and monitoring from PC to control module with USB connection (max 6 mt).

Standards

ÞElecrical Safety / EMC compatibility BS EN 60950 Electrical business equipment.
ÞBS EN 61000-6-2 EMC immunity standard.
ÞBS EN 61000-6-4 EMC emission standard.

Static Battery Charger

Þ Battery charger is manufactured with switching-mode and SMD technology and ët has high efficinecy. Battery charger models' output V-I characteristic is very close to square and output is 5 amper, 13,8 V for 12 volt and 27,6 V for 24 V . Input 198 - 264 volt AC. Proline 2405 has fully output shot circuit protection and ët can be used as a current source. Proline 1205/2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives. The charger is fitted with a protection diode across the output. Connect charge fail relay coil between positive output and CF output. They are equipped with RFI filter to reduce electrical noise radiated from the device. Galvanically isolated input and output typically 4kV for high reliability.

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories witout prior notice.

APD 33 A

Engine : Aksa
Alternator : Aksa
Control System : P 602

ASM 3 - Canopy

1 Steel structures.
2 Emergency stop push button.
3 Control panel is mounted on the baseframe . Located at the right side of the generator set
4 Corrosion-resistant locks and hinges.
5 oil could be drained via valve and a hose
6 Exhaust system in the canopy.
7 special large access doors for easy maintanance
8 Base frame -fuel tank.
9 Lifting Points.
10 sound proofing materials.

Introduction

Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet event the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies (8 - 275kVA) fit directly to the open generator set to provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

Standard Specifications

Compact footprint, low profile design.
Enclosure, generator set, exhaust system and base-tank are pre-assembled, pre-integrated and shipped as one package
Body made from steel components treated with polyester powder coating
Fire retardant foam insulation
Easy access to all service points
Exhaust system inside canopy
Large doors on each side
Control panel viewing window in a lockable access door
Emergency stop push button mounted on enclosure exterior
Cooling fan and battery charging alternator fully guarded
Fuel fill and battery can only be reached via lockable access doors.
Lifting points on the top of canopy and base frame
Customer options available to meet your applications needs.

Width	mm.	970
Lenght	mm.	1940
Height	mm.	1220
Fuel Tank Capacity	L	95

Manufacturer reserves the right to make changes in model, technical specifications, color, equipment and accessories witout prior notice.