



INTRODUCTION

Akxa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

Power (kVA)

400V, 3Phase, 50Hz, PF 0.8

VOLTAGE	STANDBY RATING (ESP)		PRIME RATING (PRP)		Standby Current (A)
	kWe	kVA	kWe	kVA	
400/230	50,0	62,0	45,0	56,0	89,5

STANDBY RATING (ESP) Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528-1. Overload is not allowed.

PRIME RATING (PRP) Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528-1. 10 % overload capability is available for a period of 1 hour within 12-hour period of operation.

General Characteristics

Model Name	APG 62
Frequency (Hz)	50
Fuel Type	Natural Gas (Pipeline)
Engine Made and Model	PSI 5.7L
Alternator	Mecc Alte
Control Panel Model	DSE 6120
Canopy	AK30

ENGINE SPECIFICATIONS

Engine	PSI
Engine Model	5.7L
Number of Cylinder	V8
Bore (mm)	101.6
Stroke (mm)	88.39
Displacement (L)	5.7
Aspiration	Naturally Aspirated
Compression Ratio	9.4:1
Engine Speed (rpm)	1500
Oil Capacity (Total With Filter) (L)	4.7
Standby Power (kWm / HP) ^{1,2,3,4} Per ISO 3046	57 / 76.4
Prime Power (kWm / HP) ^{1,2,3,4} Per ISO 3046	52 / 69.7



Block Heater QTY	1
Block Heater Power (Watt)	1500
Fuel Type	Natural Gas (pipeline)
Ignition Type	Spark-Ignited
Governor System	ECU
Operating Voltage (Vdc)	12
Battery and Capacity (Qty / Ah)	1x85
Charge Alternator (A)	180
Cooling Method	Water Cooled
Cooling Fan Air Flow (L/min) ⁵	TBD
Coolant Capacity (L)	16.6
Air Filter	Dry Type
Fuel Cons. Prime With %100 Load (kg/hr / m3/hr) ^{3,4,6}	10.8 / 15
Fuel Cons. Prime With %75 Load (kg/hr / m3/hr) ^{3,4,6}	TBD / TBD
Fuel Cons. Prime With %50 Load (kg/hr / m3/hr) ^{3,4,6}	TBD / TBD

ALTERNATOR CHARACTERISTICS

Manufacturer	Mecc Alte
Alternator Made and Model	ECP 32 2L/4A
Frequency (Hz)	50
Power (kVA)	63
Voltage (V)	400
Phase	3
A.V.R.	DSR
Voltage Regulation	(+/-)1%
Insulation System	H
Protection	IP23
Rated Power Factor	0.8
Weight Comp. Generator (kg)	277
Cooling Air (m ³ /min)	11.8

Gen.Set Dimensions

Length (mm)	2466
Width (mm)	1010
Height (mm)	1553
Dry Weight (kg)	1040

1 Max load and overload ratings based on ISO 3046 gross flywheel power.

2 Technical data based on ISO 3046-1 standards of 77°F(25°C), 14.5Psia (100kPa) and 30% relative humidity.

3 Production tolerances in engines and installed components can account for power variations of ± 5%. Altitude, temperature and excessive exhaust and intake restrictions should be applied to power calculations.

4 All fuel and thermal calculations unless otherwise noted are done at ISO 3046 rated load using LHV for NG of 48.17 MJ/kg.

5 At 0.5 in-H₂O of Package Restriction at STP

6. Volume calculated using density of 0.717 kg/m³ for NG, 0.51 kg/L for LPG



1. Steel structures made from steel sheet and steel profiles.
2. Emergency stop push button
3. Control panel is right side of the set.
4. Corrosion resistant locks and hinges.
5. Sump drains valves
6. Sound proof foam material
7. Lifting points

INTRODUCTION

Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet even the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

Control Panel

Control Module	DSE
Control Module Model	DSE 6120
Communication Ports	CANBUS



1. Menu navigation buttons
2. Close mains button
3. Main Status and instrumentation display
4. Alarm LED's
5. Close generator button
6. Status LED's
7. Operation selecting buttons

Devices

DSE, model 6120 Auto Mains Failure control module,
 Battery charger input 198-268V, output 27.6V 5A (24V) or 13.8V 5A (12V)
 Emergency stop push button and fuses for control circuits

CONSTRUCTION and FINISH

- Comonents installed in sheet steel enclosure.
- Phosphate chemical, pre-coating of steel provides corrosion resistant surface
- Polyester composite powder topcoat forms high gloss and extremely durable finish
- Lockable hinged panel door provides for easy component access



INSTALLATION

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen.Set. from Alternator).

GENERATING SET CONTROL UNIT

The DSE 6120 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts.

Module monitors the mains supply and switch over to the generator when the mains power fails.

The DSE6120 also indicates operational status and fault conditions, Automatically shutting down the Gen. Set and giving true first up fault condition of Gen. Set failure. The LCD display indicates the fault.

STANDARD SPECIFICATIONS

Microprocessor controlled

-Microprocessor controlled.

-LCD display makes information easy to read.

-Automatically transfers between mains (utility) and generator power.

-Manual programming on front panel.

-User-friendly set-up and button layout.

-Remote start.

-Event logging (50) showing date and time.

- Controls: Stop/Reset, Manual, Auto, Test, Start, buttons. An additional push button next to the LCD display is used to scroll through the modules' metering displays.

Instruments

ENGINE

Engine speed

Oil pressure

Coolant temperature

Run time Battery volts

Configurable timing

GENERATOR

Voltage (L-L, L-N)

Current (L1-L2-L3)

Frequency

Earth current

kW

Pf

kVA_r

kWh, kVA_h, kVA_rh

Phase sequence



MAINS

Voltage (L-L, L-N)

Frequency

WARNING

Charge failure

Battery under voltage

Fail to stop

Low fuel level (opt.)

kW over load

Negative phase sequence

Loss of speed signal

PRE-ALARMS

Low oil pressure

High engine temperature

Low engine temperature

Over /Under speed

Under/over generator frequency

Under/over generator voltage

ECU warning

SHUT DOWNS

Fail to start

Emergency stop

Low oil pressure

High engine temperature

Low coolant level

Over /Under speed

Under/over generator frequency

Under/over generator voltage

Oil pressure sensor open

Phase rotation

ELECTRICAL TRIP

Earth fault

kW over load

Generator over current

Negative phase sequence

**Options**

High oil temperature shut down

Low fuel level shut down

Low fuel level alarm

High fuel level alarm

EXPANSION MODULES

Editional LED module (2548)

Expension relay module (2157)

Expansion input module (2130)

Standards

Electrical Safety / EMC compatibility

BS EN 60950 Electrical business equipment

BS EN 61000-6-2 EMC immunity standard

BS EN 61000-6-4 EMC emission standard

STATIC BATTERY CHARGER

Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.

Battery charger models' output V-I characteristic is very close to square

2405 has fully output shot circuit protection and it can be used as a current source.

2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives.

The charger is fitted with a protection diode across the output.

Charge fail output is available.

Connect charge fail relay coil between positive output and CF output.

Input: 196-264V.

Output: 27,6V 5A or 13,8V 5A.

STANDARD SPECIFICATIONS

- Heavy duty, water cooled naturalgas engine
- 46/50 °C ambient rated radiator with mechanical fan
- Protective grille for fan and rotating parts
- Electric starter and charge alternator
- Starting battery (with lead acid) including rack and cables
- Engine jacket cooling heater
- Static battery charger
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel belows supplied separately
- Manual for use and installation

**OPTIONAL EQUIPMENTS****ENGINE**

Remote Radiator Cooling

ALTERNATOR

Anti-Condensation heater

Over sized alternator

Main line circuit breaker

CONTROL SYSTEM

Remote annunciator panel

Remote alarm panel

Alarm output relays

Earth fault, single set

Charging ammeter

TRANSFER SWITCH

Three Pole Contactor

Four Pole Contactor

WISE ACCESSORIES

Manuel oil drain pump

Electrical oil drain pump

Enclosure: weathe protective or sound attenuated

Duct adapter (on radiator)

Inlet and outlet motorised louvers

Tool kit for maintenance

Supplied with oil and coolant- 30 °C

AKSA CERTIFICATES

- CE
- 2000/14/EC